HDMI TO TVI VIDEO CONVERTER

Model No: TVI-ER03HR

Operating Instruction

FEATURES

- Detect the HDMI EDID information automatically.
- Receive the HDMI video then converter to TVI output and HDMI loop output.
- HDMI video input supports:
 1280x720,800x600,1024x768,1280x1024,1440x900,1920x1080.
- The output of TVI supports 720P or 1080P 30/25Hz. When the resolution of HDMI input is 800x600,1024x768,1280x720, the TVI output is 720P, when is other resolution, the TVI output is 1080P.
- The resolution of HDMI loop output is same as the HDMI input.
- With POWER LED and RUN LED.

SPECIFICATIONS

| Model No. | TVI-ER03HR |
|---------------------|--|
| Video Input | 1-ch HDMI |
| Video Output | TVI-(720P or 1080P/30Hz) & HDMI LOOP OUT |
| Power Supply | DC 12V/1A |
| Consumption | ≤3W |
| Working Temperature | -10 °C ~ +55 °C |
| Working Humidity | 10% ~ 90% |
| Dimension | 120 × 80 × 26 mm (4.72"x3.15"x1.02") |
| Weight | ≤0.225kg |

PANEL DESCRIPTIONS

| VIDEO OUT | DC12V/1A |
|-----------|------------------|
| | |
| POW O | HDMI OUT HDMI IN |

CONNECTING AND OPERATING

- 1) Connect the HDMI source into the HDMI IN.
- 2) Connect the TVI output to TVI receive device.
- 3) Connect power adapter into the device. For a moment, when the RUN LED is flashing, the device works normally.

PACKING CONTENTS

- 1) HDMI TO TVI Converter
- 2) Operating Instructions
- 3) Power adapter DC 12V/1A

MAINTENANCE

Clean the unit with a soft, dry cloth, never use alcohol, paint thinner of benzene to clean the unit.

Dear Customer

Thank you for purchasing this product, for optimum performance and safety, please read these instructions carefully before connecting, operating this product. Please keep the manual for future reference.